



LinkPlus Key-Mapping Grid

Link Wireless Telephone System
NetLink Wireless Telephone System

A promotional banner for TRC Telecom Resource Corporation. On the left is the TRC logo, which includes the letters "TRC" in a large, bold, blue font, with "TELECOM RESOURCE CORPORATION" in a smaller font below it, and the website "trcnetworks.com" at the bottom. To the right of the logo is a man in a suit wearing a headset. The background is a light blue gradient with a subtle pattern of concentric circles. Text on the banner includes "Have A Question? Need More Info?" and "Call Us: 1 877 390 1166".

TRC
TELECOM RESOURCE
CORPORATION
trcnetworks.com

Have A Question?
Need More Info?

Call Us: 1 877 390 1166

Part Number: 72-0070-20
Issue B

NOTICE

SpectraLink Corporation has prepared this document for use by SpectraLink personnel and clients. The drawings and specifications contained herein are the property of SpectraLink and shall be neither reproduced in whole or in part without the prior written approval of SpectraLink, nor be implied to grant any license to make, use, or sell equipment manufactured in accordance herewith.

SpectraLink reserves the right to make changes in specifications and other information contained in this document without prior notice, and the reader should in all cases consult SpectraLink to determine whether any such changes have been made.

The terms and conditions governing the sale of SpectraLink hardware products and the licensing of SpectraLink software consist solely of those set forth in the written contracts between SpectraLink and its customers. No representation or other affirmation of fact contained in this document including but not limited to statements regarding capacity, response-time performance, suitability for use, or performance of products described herein shall be deemed to be a warranty by SpectraLink for any purpose, or give rise to any liability of SpectraLink whatsoever.

In no event shall SpectraLink be liable for any incidental, indirect, special, or consequential damages whatsoever (including but not limited to lost profits) arising out of or related to this document, or the information contained in it, even if SpectraLink has been advised, knew, or should have known of the possibility of such damages.

Trademark Information

SpectraLink

LinkPlus

Link Wireless Telephone System

NetLink Telephony Gateway

NetLink Wireless Telephone

NetLink SVP Server

SpectraLink Voice Priority

ccLink Wireless Telephone System

are trademarks and registered trademarks of SpectraLink Corporation.

All other trademarks used herein are the property of their respective owners.

LinkPlus Key-Mapping Grid

© 2002 SpectraLink Corporation.

All Rights Reserved

Printed in the United States of America

<p>SpectraLink Corporation 5755 Central Avenue Boulder, CO 80301 Within the United States, dial 303.440.5330 or toll free 800.676.5465 Outside the U.S., dial +1.303.440.5330 www.spectralink.com</p>

LinkPlus Key-Mapping Grid

This document is intended to be a succinct reference for button mapping wireless telephones to emulate wired sets provided by specified vendors.

Key sequences are shown on the left column. Each vendor column displays the default and programmable settings for the wireless phone as mapped against the wired set provided by the vendor.

Please refer to the appropriate *LinkPlus Interface Guide* for specific directions and required settings.

Key

Bold	Programmed to display on Wireless Telephone menu(default)
Regular	Mapping per 72-0170-xx
	Not available per 72-0170-xx
(blank)	* No data in 72-0170-xx
	Not released

	Analog*	Comdial	Definity	Executone	Fujitsu	Intertel	Intertel
MODEL		80212S	8410D	MODEL32	F9600	Axxent	Eclipse
FCN+1	Mute	Mute	Mute	Mute	Mute	Mute	Mute
FCN+2	Xfer	Fwd	Xfer	TR/CON	Camp On	Fwd	Fwd
FCN+3	Conn	Pick	Conf		Flash	Line10	
FCN+4	Conf	Page	Drop	10-QuickDial	FAB10	Line11	
FCN+5	Fwd	ShftBtn4	LND	11-QuickDial	FAB11	CNF	CNF
FCN+6	Redial	ShftBtn5	AbDial	12-QuickDial	New Call	Msg	Msg
FCN+7	Pick	ShftBtn7	Vmail	Prog	Park	REDL	REDL
FCN+8	Camp	Exit Menus	CallBk	VM/MSG	Xfer	Trans	Trans
FCN+9	Exit Menus	Trnf/ Cnf	Exit Menus	Exit Menus	FAB12	SYSPD	SYSPD
FCN+0		Page/ Softkey2					
FCN+#		Softkey3		15	Exit Menus	SPCL	SPCL
FCN+*		Softkey1		18	FAB13	Exit Menu	Exit Menu
START	Flash	Flash		Start	Start	Start	Start
END	End	End	End	End	End	End	End
HOLD	Hold	Hold	Hold	Hold	Hold	Hold	Hold
Line+1		LINE 1	Btn 1	01-Line1	FAB00	Line1(Call1)	Line1(Call1)
Line+2		LINE 2	Btn 2	02-Line2	FAB01	Line2(Call2)	Line2(Call2)
Line+3		LINE 3	Btn 3	03-Line3	FAB02	Line3(Call3)	Line3(Call3)
Line+4		LINE 4	Btn 4	04-Line4	FAB03	Line4(Call4)	Line4(Call4)
Line+5		LINE 5	Btn 5	05-Line5	FAB04	Line5(IC)	Line5(IC)
Line+6		LINE 6	Btn 6	06-Line6	FAB05	Line6(DND)	Line6(DND)
Line+7		LINE 7		07-QuickDial	FAB06	Line7	Line7
Line+8		LINE 8		08-QuickDial	FAB14	Line8	Line8
Line+9		Intercom		09-QuickDial	FAB15	Line9	Line9
Line+0		Speaker			Release		
Line+*							
Line+#							
FCN*1			Softkey1				
FCN*2			Softkey2				
FCN*3			Softkey3				
FCN*4			Softkey4				
FCN*5			Menu				
FCN*6			Exit				
FCN*7			Prev				
FCN*8			Next				

	Meridian	Merlin	Mitel	NEC	Norstar	Panasonic	Rolm	Toshiba
Model	M2616	Legend	420	NEAX	M7310	DBS	400	2020-SD
FCN+1	Mute	Mute	Mute	Mute	Mute	Mute	Mute	Mute
FCN+2	Xfer	Xfer	Xfer/Cnf	Trf	Xfr	Prog	Xfr	Cnf/Xfr
FCN+3	Conf	Conf	Redial	Cnf	Conf	Conf	Conn	Redial
FCN+4	LastNo	LND	Msg	Lnr/Spd	LastNo	Redial	Conf	Msg
FCN+5	Fwd	Fwd		Recall	Fwd	Mode	Fwd	Fwd
FCN+6	Msg	Page		FCN Key1	Speed	End	SvRpt	Speed
FCN+7	Pick	Pick	L/S Key 10	FCN Key2	Pick	->	Pick	Pick
FCN+8	RingAgn	Callbk	L/S Key 11	FCN Key3	Page	<-	Camp	Page
FCN+9	Exit Menus	Exit Menus	Exit Menus	FCN Key4	Exit Menus	Exit FCN Menu	Exit Menus	Exit Menus
FCN+0		Feature	Middle Softkey	Fnc	Page		DND	Page
FCN+#			Right Softkey				StaSp	Scroll
FCN+*			Left Softkey	Exit Menus		Auto		Mode
START	Start	Start	Start	Start	Start	Flash	Flash	Start
END	End	End	End	End	End	End	End	End
HOLD	Hold	Hold	Hold	Hold	Hold	Hold	Hold	Hold
Line+1		Btn1	L/S Key 1	LINE 1	LineBtn1	FF1	LINE 1	CO1
Line+2		Btn2	L/S Key 2	LINE 2	LineBtn2	FF2	LINE 2	CO2
Line+3		Btn3	L/S Key 3	LINE 3	LineBtn3	FF3	LINE 3	CO3
Line+4		Btn4	L/S Key 4	LINE 4	LineBtn4	FF4	LINE 4	CO4
Line+5		Btn5	L/S Key 5	LINE 5	LineBtn5	FF5	LINE 5	CO5
Line+6		Btn6	L/S Key 6	LINE 6	LineBtn6	FF6	LINE 6	CO6
Line+7		Btn7	L/S Key 7	LINE 7	LineBtn7	FF7	LINE 7	CO7
Line+8		Btn8	L/S Key 8	LINE 8	LineBtn8	FF8	LINE 8	CO8
Line+9		Btn9	L/S Key 9	LINE 9	LineBtn9		LINE 9	Intercom
Line+0	Rls	Drop	Cancel		Rls	FF11		Spkr
Line+*			Superkey		Feature	FF10		
Line+#						FF12		
FCN*1								
FCN*2								
FCN*3								
FCN*4								
FCN*5		Home						
FCN*6		Menu						
FCN*7		Inspct						
FCN*8		More						

	Siemens	Siemens
Model	Hicom 150	Hicom 300
FCN+1	Mute	Mute
FCN+2	(voice mail)	(voice mail)
FCN+3		
FCN+4		
FCN+5		
FCN+6		
FCN+7		
FCN+8		
FCN+9	Exit Menus	Exit Menus
FCN+0		Select
FCN+#		Previous
FCN+*		Next
START	Start	Start
END	End	End
HOLD	Hold	Hold
Line+1		
Line+2		
Line+3		
Line+4		
Line+5		
Line+6		
Line+7		
Line+8		
Line+9		
Line+0		
Line+*		
Line+#		
FCN*1		
FCN*2		
FCN*3		
FCN*4		
FCN*5		
FCN*6		
FCN*7		
FCN*8		